

USask Master Specification Directions: The master specifications are intended to be incorporated into the Consultant's final, project specific specification package. The project specific specifications are expected to include any and all sections or portions of sections (Part 1, Part 2, Part 3) that are required to create a fully executable project specification. USask Master Specs only provide information that USask **requires** be a part of the final specification package. Components or sections not included in the Master USask Specifications may still be required for a complete, well-designed project. **It is the consultant's responsibility to ensure all specifications match USask requirements. Any deviations or revisions to any section included in the master specifications requires written consent from the USask Engineering department. The consultant is liable for any omissions, errors, or incorrect equipment or components supplied to site.**

The Master Specifications shall be used in conjunction with USask's Design Guidelines. Any conflicts shall be brought to the attention of USask Engineering staff for clarification.

Part 1 General

Part 2 Products

2.1 GENERAL

- .1 Motors: premium efficiency, in accordance with applicable Codes and standards, and to ASHRAE 90.1 and NECB.

2.2 MOTORS

- .1 Provide motors for mechanical equipment as specified.
- .2 Refer to electrical division for voltage and phase requirements for different HP sizes.
 - .1 ECM motors may be acceptable for voltages up to and including 208V.

2.3 BELT DRIVES

- .1 Fit reinforced belts in sheave matched to drive. Multiple belts to be matched sets.
- .2 Use cast iron or steel sheaves secured to shafts with removable keys unless otherwise indicated.
- .3 For motors under 10 HP: standard adjustable pitch drive sheaves, having plus or minus 10% range. Use mid-position of range for specified r/min.
- .4 For motors 10 HP and over: sheave with split tapered bushing and keyway having fixed pitch unless specifically required for item concerned. Provide sheave of correct size to suit balancing.
- .5 Correct size of sheave determined during commissioning.
- .6 Minimum drive rating: 1.5 times nameplate rating on motor. Keep overhung loads within manufacturer's design requirements on prime mover shafts.
- .7 Motor slide rail adjustment plates to allow for centre line adjustment.
- .8 Supply one set of spare belts for each set installed.

2.4 DRIVE GUARDS

- .1 Provide guards for all drives including drives and fans within fan plenums.
- .2 Guards for belt drives:
 - .1 Expanded metal screen welded to steel frame.
 - .2 Minimum 1.2 mm thick sheet metal tops and bottoms.
 - .3 38 mm dia holes on both shaft centres for insertion of tachometer.
 - .4 Removable for servicing.
- .3 Provide means to permit lubrication and use of test instruments with guards in place.
- .4 Install belt guards to allow movement of motors for adjusting belt tension.
- .5 Guard for flexible coupling:
 - .1 "U" shaped, minimum 1.6 mm thick galvanized mild steel.
 - .2 Securely fasten in place.
 - .3 Removable for servicing.
- .6 Unprotected fan inlets or outlets:
 - .1 Wire or expanded metal screen, galvanized, 19 mm mesh.
 - .2 Net free area of guard: not less than 80% of fan openings.
 - .3 Securely fasten in place.
 - .4 Removable for servicing.

Part 3 Execution

END OF SECTION